

SPECIFICATIONS

| 50Hz (1500rpm) | | | | | | | | |
|----------------|----------------|----------|--------------|------|------|------|-----|--|
| MGS MODEL | ENGINE MODEL | VOLTAGE | OUTPUT (KVA) | | | | | |
| | | | ESP | CP | PRP | DCCP | CDP | |
| MGS3100R | S16R2-PTAWT-CR | 380-415V | 3025 | 2750 | | | | |
| MGS2800B | S16R2-PTAW2-S | 380-415V | | 2750 | | 2500 | | |
| MGS2500R | S16R2-PTA | 380-415V | 2500 | 2250 | 1900 | | | |
| MGS2300R | S16R-PTA3 | 380-415V | 2250 | 2050 | 1745 | | | |
| MGS2000R | S16R-PTAR | 380-415V | 2000 | 1800 | 1550 | | | |
| MGS1700R | S12R-PTA3 | 380-415V | 1650 | 1500 | 1110 | | | |
| MGS1500R | S12R-PTAR1 | 380-415V | 1500 | 1380 | | | | |
| MGS0900R | S6R2-PTA2 | 380-415V | 880 | 800 | 680 | | | |
| MGS0800R | S6R2-PTAR | 380-415V | 780 | 700 | 550 | | | |
| MGS0700R | S6R-PTAR | 380-415V | 690 | 625 | 500 | | | |
| MGS0600R | S6A3-PTAA | 380-415V | 555 | 505 | | | | |
| MGS0500R | S6A3-PTAR | 380-415V | 505 | 460 | 385 | | | |